

## WD-01

### UHF Antenna Divider



#### Overview

- Provides diversity output for up to six receivers
- Power supplied to the Sony UHF antenna
- Cascade output can be used for an additional antenna-divider or receiver
- Two pairs of antenna input connectors to expand the operating area of a wireless microphone system

#### Specifications

##### General

Frequency Range	US : 470 to 616 MHz CE : 470 to 714 MHz
-----------------	--

Channel Distribution	Inputs: 2 pairs Outputs: 6 pairs
----------------------	-------------------------------------

Antenna Input/Output	BNC-R, 50 ohms
----------------------	----------------

Cascade Output	1 pair
----------------	--------

Power Supply for Antenna Booster (supplied from	DC 9 V / THRU / 12 V
---	----------------------

antenna input  
connectors)

Power Requirements	US: AC 120 V CE: AC 220 to 240 V
--------------------	-------------------------------------

Power Consumption	18 W (when supplying 160mA to antenna booster)
-------------------	--

Dimensions (W x H x D)	Approx. 483 × 44 × 285 mm (19 1/8 inch x 1 3/4 x 11 1/4 inches)
------------------------	--

Mass	Approx. 3.3 kg (7 lb 4.4 oz)
------	------------------------------

## Supplied Accessories

Audio Output Connector	Power cord (1) Before Using This Unit (1) Warranty booklet (1)
------------------------	--

## Related products



### **DWR-R03D**

DWX Series 2-channel  
digital wireless  
receiver

## Gallery

