

WD-01

UHF Antenna Divider



Overview

- Provides diversity output for up to six receivers
- Power supplied to the Sony UHF antenna
- Cascade output can be used for an additional antenna-divider or receiver
- Two pairs of antenna input connectors to expand the operating area of a wireless microphone system

Specifications

General

Frequency Range	US : 470 to 616 MHz CE : 470 to 714 MHz
Channel Distribution	Inputs: 2 pairs Outputs: 6 pairs
Antenna Input/Output	BNC-R, 50 ohms
Cascade Output	1 pair
Power Supply for Antenna Booster (supplied from antenna input connectors)	DC 9 V / THRU / 12 V
Power Requirements	US: AC 120 V CE: AC 220 to 240 V
Power Consumption	18 W (when supplying 160mA to antenna booster)
Dimensions (W x H x D)	Approx. 483 × 44 × 285 mm (19 1/8 inch x 1 3/4 x 11 1/4 inches)
Mass	Approx. 3.3 kg (7 lb 4.4 oz)

Supplied Accessories

Audio Output Connector	Power cord (1) Before Using This Unit (1) Warranty booklet (1)
------------------------	--

Information on EU Data Act: [Click here](#) to check if your Sony product and/or related service is subject to the EU Data Act.

Related products



DWR-R03D

DWX Series 2-channel digital
wireless receiver

Gallery



© 2004 - 2026 Sony Corporation. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Features and specifications are subject to change without notice. The values for mass and dimension are approximate. All trademarks are the property of their respective owners.