BKM-250TGM 3G/HD/SD-SDI Input Adaptor



Overview

Input adaptor for LMD-3251MT, LMD-3251TC, LMD-2451MT, LMD-2451TC, LMD-2451MD, LMD-2451MC, PVM-2551MD, PVM-2551MC, LMD-1951MD, LMD-1951MC.

This 3G-SDI interface board for LMD-3251MT, LMD-3251TC, LMD-2451MT, LMD-2451TC, LMD-2451MD, LMD-2451MC, PVM-2551MD, PVM-2551MC, LMD-1951MD, LMD-1951MC medical monitors is compliant with the SMPTE 425 standard. It requires only a single SDI cable to transmit up to 10-bit 4:2:2 1080P/60P video signals.

Specifications

Input

BNC (x2) Input impedance: 75 ohms unbalanced Sampling frequency 3G-SDI: Y/Cb/Cr (4:2:2) 148.5 MHz/74.25 MHz/74.25 MHz Y/Cb/Cr (4:4:4) 148.5 MHz/148.5 MHz/148.5 MHz

	G/B/R
SDI Input	148.5 MHz/148.5 MHz/148.5 MHz
	HD-SDI:
	Y/Cb/Cr 74.25 MHz/37.125
	MHz/37.125 MHz
	SD-SDI:
	Y/Cb/Cr:13.5 MHz/6.75 MHz/6.75
	MHz
	Quantization
	3G-SDI: 10 bits/sample, 12
	bits/sample
	HD-SDI: 10 bits/sample
	SD-SDI: 10 bits/sample
Output impedance:	75-ohms unbalanced

Output	
SDI Output	3NC (x1) (monitor output) *1 Output signal amplitude: 800 mVp- o ±10% Output impedance: 75 ohms unbalanced Transmission distance HD-SDI: 100 m (approx.328 ft) max. *2 SD-SDI: 200 m (approx.656 ft) max. *3

Timecod		
IIIIECOU	ופ טואן	лау

Available Standard	SMPTE-12M-2
Timecode Type	VITC, LTC

Audio Level Meter Display

Channel	CH1 to CH8 or CH9 to CH16
Level	-60 dB to -0.01dB
Color	-0.01 dB to 0 dB: Red -1.25 dB to -0.01 dB: Orange -20 dB to 1.25 dB: Yellow -60 dB to -20 dB: Green

General	
Voltage	+3.3 V, +5 V DC (supplied from the main unit)
Power Consumption	Approx. 4.0 W
Operating Temperature	0°C to 35°C (Recommended: 20°C to 30°C) 32°F to 95°F (Recommended: 68°F to 86°F)

Operating Humidity	0% to 90% (no condensation)
Storage/Transport Temperature	-20°C to +60°C -4°F to +140°F
Storage/Transport Humidity	0% to 90%
Operating/Storage/Transport Pressure	700 hPa to 1060 hPa
Dimensions (W x H x D) *4	100 x 20 x 162 mm 4 x 13/16 x 6 1/2 inches
Mass	Approx. 270 g Approx. 9.5 oz
Supplied Accessories	Operating Instructions (1)
*1	The signal from the monitor output
*2	When using 5C-FB coaxial cables (Fujikura or equivalent).
*3	When using 5C-2V coaxial cables (Fujikura or equivalent).
*4	The values for dimensions are approximate.



Gallery



© 2004 - 2024 Sony Corporation. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Features and specifications are subject to change without notice. The values for mass and dimension are approximate. All trademarks are the property of their respective owners.