

## ECM-674

Affordable shotgun Electret condenser microphone



### Overview

The ECM-674 is an affordable shotgun-type electret condenser microphone, which delivers excellent sound performance in field and studio productions.

#### **Superb Sound Quality**

The ECM-674 offers an excellent sensitivity of -36 dB (0 dB=1 V/Pa.) and low inherent-noise level of less than 17 dB SPL. This allows the microphone to be used for clear voice pick-up even in noisy environments

#### **Two-way Powering**

A two-way powering capability allows the ECM-674 to be driven by microphone power or batteries, making it suitable for both camcorder mounting and many other sound-gathering applications. Internal: AA-size battery operation. External: DC (40 to 52 V) operation

#### **Built-in Battery Liquid Leakage Protection Circuit**

In general, old batteries can leak and damage the equipment they are used in. The ECM-674 prevents this by continually detecting the output voltage of the battery and shutting off the power supplied to the electric circuit whenever the voltage drops beneath a certain threshold.

## Features

### **Flat-and-wide Frequency Response**

The ECM-674 microphone has a flat-and-wide frequency response (40 Hz to 20 kHz) and provides sound reproduction that is extremely smooth and natural

### **Compact and Lightweight Design**

The ECM-674 has been designed as a highly directional compact and lightweight shotgun microphone. It measures only 268 mm (10 5/8 inches) in length and weighs just 185 g (6.5 oz), maintaining good balance even when mounted on compact camcorders.

### **Built-in Low Cut Filter**

The built-in two-position (M, V) low-cut switch provides users with a simple method of reducing the effects of undesired ambient noise.

## Specifications

### Audio Section

Capsule Type	Mono Electret Condenser
Frequency Response	40 Hz to 20 kHz
Directivity	Uni-directional (super-cardioid)
Sensitivity *[1]	-36 dB $\pm$ 3 dB
Output Impedance * [2]	220 $\Omega$ $\pm$ 20%, Balanced
Dynamic Range	Phantom: 107 dB or more Battery: 98 dB or more
Signal-to-Noise Ratio	

*[3]	77 dB or more
Inherent Noise *[4]	17 dB SPL or less
Induction Noise From External Magnetic Field *[5]	0 dB SPL or less
Wind Noise *[6]	50 dB SPL (without windscreen) 45 dB SPL or less (with windscreen)
Maximum Input Sound Pressure Level *[7]	Phantom: 124 dB SPL Battery: 115 dB SPL

## General Section

Connector	XLR-3-12C (male)
Mic Cable	XLR-3 to XLR-3 500 mm 19.6 inches
Power Requirements	External: DC 40 V to 52 V Battery: 1.5 V
Dimensions *[8]	φ20 x 268 mm φ13/16 x 10 5/8 inches
	Approx. 7.3 oz with battery Approx. 6.5 oz without battery

Mass	Approx. 208 g with battery Approx. 185 g without battery
------	---

Supplied Accessories	<ul style="list-style-type: none"> <li>Windscreen (1)</li> <li>Stand adaptor (2)</li> <li>Short XLR cable</li> <li>Operating instructions (1)</li> <li>Mic spacer (2)</li> <li>Mic holder (1)</li> </ul>
----------------------	--

## Notes

Note	<ul style="list-style-type: none"> <li>*[1] 0 dB = 1 V/Pa, at 1 kHz</li> <li>*[2] Output impedance at 1 kHz</li> <li>*[3] A-weighted, 1 kHz, 1 Pa.</li> <li>*[4] 0 dB SPL = 20 <math>\mu</math>Pa.</li> <li>*[5] dB SPL/1E-7 T, 0 dB SPL = 20 <math>\mu</math>Pa.</li> <li>*[6] Wind noise at 2m/s (0 dB SPL = 20 <math>\mu</math>Pa.)</li> <li>*[7] 0 dB SPL = 20 <math>\mu</math>Pa.</li> <li>*[8] The values for dimensions are approximate.</li> </ul>
------	--

Related products



## **HXC-FB80**

Three 2/3-inch  
Exmor™ CMOS sensor  
HD colour studio  
camera

## Gallery

