

## WD-01

### UHF Antenna Divider



#### Overview

- Provides diversity output for up to six receivers
- Power supplied to the Sony UHF antenna
- Cascade output can be used for an additional antenna divider or receiver
- Two pairs of antenna input connectors to expand the operating area of a wireless microphone system

#### Specifications

##### General

Rango de frecuencia	US: 470 to 616 MHz CE: 470 to 714 MHz
---------------------	--

Distribución de canales	Inputs: 2 pairs Outputs: 6 pairs
-------------------------	-------------------------------------

Entrada/salida de la antena	BNC-R, 50 ohms
-----------------------------	----------------

Salida en cascada	1 pair
-------------------	--------

Fuente de alimentación para el	
--------------------------------	--

amplificador de la antena br(se suministra desde los conectores de entrada de antena)	DC 9 V / THRU / 12 V
Requisitos de alimentación	US: AC 120 V CE: AC 220 to 240 V
Consumo eléctrico	18 W (when supplying 160 mA to antenna booster)
Dimensiones (An. x Al. x Prof.)	Approx. 483 × 44 × 285 mm (19 1/8 inch x 1 3/4 x 11 1/4 inches)
Peso	Approx. 3.3 kg (7 lb 4.4 oz)

## Supplied Accessories

Conector de salida de audio	Power cord (1) Before Using This Unit (1) Warranty booklet (1)
-----------------------------	--

## Related products



### **DWR-R03D**

DWX Series 2-channel digital wireless receiver

## Gallery

