

## WD-850

### UHF Antenna Divider



#### Overview

- Provides diverse output for up to four receivers/tuner base units
- Power supplied to the Sony UHF Antenna
- Cascade output can be used for an additional antenna divider or receiver/tuner base unit
- Two pairs of antenna input connectors to expand the operating area of a wireless microphone system

#### Specifications

##### Group heading

Frequency range	US: 470 to 806 MHz CE: 470 to 862 MHz J: 770 to 810 MHz
-----------------	---

Channel distribution	Inputs: 2 pairs Outputs: 4 pairs
----------------------	----------------------------------

Antenna input/output	BNC-R, 50 ohms
----------------------	----------------

Cascade output	1 pair
----------------	--------

Power supply for antenna booster	
----------------------------------	--

(supplied from antenna input connectors)	DC 9 V/OFF switchable
Power requirements	US: 120 V AC, 60 Hz CE: 230 V, 50 Hz J: 100 V AC, 50 Hz / 60 Hz
Power consumption	18 W (when 100 mA is being supplied to the antenna booster)
Dimensions (W x H x D)	19 x 1.75 x 11.25 inches (Approx. 482 x 44 x 285 mm)
Mass	Approx. 4.4 kg (9 lb 11 oz)

## Supplied Accessories

Audio output connector	50 ohms terminator (6) AC power cord (1) Operating Instructions (1)
------------------------	---

## Related products



**DWR-R03D**  
DWX Series 2-channel digital wireless receiver

## Gallery

