

## AN-01

### Uni-directional UHF Antenna



### Overview

- The AN-01 is a uni-directional UHF Antenna, designed to be used with Sony analogue or digital wireless microphone systems.
- Two AN-01 should be used for diversity reception.
- A single AN-01 can receive a wide frequency range from 470 to 862MHz.
- Either DC 9V or 12V can be used for powering.
- Selectable booster gain (18 dB/10 dB/0 dB).
- The antenna is a log-periodic dipole array.
- It is supplied with a hand grip that supports screw mounting onto a microphone stand.

### Specifications

#### Antenna Section

Antenna Type	Log periodic dipole array
Directivity	Unidirectional
Frequency Range	470 MHz to 862 MHz
Antenna Gain	5 dBi or more

Voltage Standing Wave Ratio	2.5 or less
-----------------------------	-------------

Half Power Angle	150 degrees or less
------------------	---------------------

Front To Back Ratio	12 dB or more
---------------------	---------------

## Booster Section

Frequency Range	470 to 862 MHz
-----------------	----------------

Booster Gain	18 dB/10 dB/0 dB, switchable
--------------	------------------------------

Voltage Standing Wave Ratio	3.0 or less
-----------------------------	-------------

Noise Figure	6 dB or less
--------------	--------------

Third Order Intermodulation	60 dB or more (95 dB $\mu$ VEMF input)
-----------------------------	--

## Input/Output

Output Connector	BNC-R, 50 $\Omega$
------------------	--------------------

## General

Power Requirements	9 V/12 V DC
--------------------	-------------

Power Consumption	100 mA or less
-------------------	----------------

Operating	32°F to 122°F
-----------	---------------

Temperature	0°C to 50°C
Storage/Transport Temperature	-4°F to +140°F -20°C to +60°C
Dimensions *[1]	343 x 341 x 36 mm (excluding microphone stand attachment pole/grip) (W x H x D) 13 1/2 x 13 5/8 x 1 7/16 inches (excluding microphone stand attachment pole/grip) (W x H x D)
Mass	Approx. 530 g Approx. 19 oz
Supplied Accessories	Warranty card (1) Warranty booklet (1) Stand Adapter PF1/2 to W5/8 type (1) Stand Adapter PF1/2 to W3/8 type (1) Operating Instructions (1) Microphone stand attachment pole/grip (1 set)

## Notes

Note \*[1] The values for dimensions are approximate.

Related  
products



## **DWR-R03D**

DWX Series 2-channel  
digital wireless  
receiver

## Gallery

