

## DWA-F03D

Digital Wireless Adaptor



### Overview

The DWA-F03D is an expandable adaptor for the DWR-S03D digital slot-in wireless receiver. Designed to fit in mixer bags for ENG / EFP applications, this model offers lightweight and compact operation.

### Features

#### **Lightweight solution for mixer bag operation**

Use the DWA-F03D in combination with the DWR-S03D as a stand-alone two-channel digital receiver. The DWA-F03D offers the added value of being lightweight and compact for mixer bag operation.

#### **Two-way power options**

The DWA-F03D is equipped with both a Hirose 4 pin connector and a USB Type-C power supply connector. For mixer bag use with battery systems, achieve centralised management using either the Hirose 4 pin or the USB Type-C connector. Power your device from external sources, such as mobile batteries, with the USB connector.

### Specifications

#### Audio Section

SMC9-4S (female) (x2)

Analog Output

Output Impedance: 150  $\Omega$  or less

## General

Power Requirement DC IN: DC 10V-17V  
USB: DC 5V

Operating Temperature 32°F to 122°F  
0°C to 50°C

Storage/Transport Temperature -4°F to +140°F  
-20°C to +60°C

Dimensions 74 x 59 x 42 mm  
3 x 2 3/8 x 1 11/16 inches

Mass Approx. 110 g  
Approx. 3.9 oz

Supplied Accessories Warranty booklet (1)  
Before Using This Unit (1)  
Audio cable (2)

## Related products



### **DWR-S03D**

DWX Gen3 2-channel digital wireless slot-in receiver

## Gallery

