

AC-DN2B

AC Adapter (150W output) and
Lithium-Ion battery charger



Overview

This AC adapter clips to the rear of many Sony camcorders. In addition it can, either in stand-alone mode or simultaneously, charge Lithium-Ion batteries.

Specifications

Generic Specifications

| | |
|--------------------|-----------------|
| Power requirements | AC 100 to 240 V |
|--------------------|-----------------|

| | |
|-------------------------|-------|
| Rated power output (DC) | 150 W |
|-------------------------|-------|

| | |
|---------------------|--------|
| Voltage output (DC) | 16.7 V |
|---------------------|--------|

| | |
|---------------------|---------------------|
| Current output (DC) | 9 A (on regulation) |
|---------------------|---------------------|

| | |
|------|--------------------|
| Mass | 950 g (2 lb. 2 oz) |
|------|--------------------|

| | |
|------------|--|
| Dimensions | 101(W) x 169(H) x 70(D)mm (4 x 6 3/4 x 2 7/8 inches) |
|------------|--|

| | |
|------------------------|-----------------------------|
| Charging time: BP-L60A | 4 h (to about 85% capacity) |
|------------------------|-----------------------------|

Charging time: BP- L90A 6 h (to about 85% capacity)

Supplied Accessories

DC power cord (1)

Operation manual (1)

Related products



HXC-FB80

Three 2/3-inch
Exmor™ CMOS sensor
HD colour studio
camera

Gallery

